

```

#include <Wire.h> // Wire Bibliothek hochladen;
#include <LiquidCrystal_I2C.h> // LiquidCrystal_I2C //Bibliothek hochladen;
LiquidCrystal_I2C lcd(0x27, 16, 2); //Displaytyp und Zeichenumfang 16 Zeichen in 2 Zeilen

int i, channel[6], rcValue[6], test;
#define SUMD_MAXCHAN 6
#define SUMD_BUFFSIZE SUMD_MAXCHAN*2 + 5
static uint8_t sumdIndex=0;
static uint8_t sumdSize=0;
static uint8_t sumd[SUMD_BUFFSIZE]={0};

void setup(){
    lcd.begin();           // LCD wird gestartet
    Serial.begin(115200);
}

void loop() {
    while (Serial.available()) {
        int val = Serial.read();
        test = val;
        if(sumdIndex == 0 && val != 0xA8) {continue; }
        if(sumdIndex == 2) {sumdSize = val;}
        if(sumdIndex < SUMD_BUFFSIZE) {sumd[sumdIndex] = val;}
        sumdIndex++;
        if(sumdIndex == sumdSize*2+5)
        { sumdIndex = 0;
        if (sumdSize > SUMD_MAXCHAN) sumdSize = SUMD_MAXCHAN;
        for (uint8_t b = 0; b < sumdSize; b++){
            rcValue[b] = ((sumd[2*b+3]<<8) | sumd[2*b+4])>>3;
            if (rcValue[b] > 750 && rcValue[b] < 2250){channel[b] = rcValue[b];} //filter
        }
    }
}

debug();
}

void debug(){
//  lcd.setCursor(0,0);
//  lcd.print(test);
//  delay(1000);
    lcd.setCursor(0,0);
    // lcd.print("          ");
    lcd.setCursor(0,0);
    lcd.print(channel[0]);
    lcd.setCursor(5,0);
    lcd.print(channel[1]);
    lcd.setCursor(10,0);
    lcd.print(channel[2]);
    lcd.setCursor(0,1);
    // lcd.print("          ");
    lcd.setCursor(0,1);
    lcd.print(channel[3]);
    lcd.setCursor(5,1);
    lcd.print(channel[4]);
    lcd.setCursor(10,1);
    lcd.print(channel[5]);

delay(50);
}

```